

AeGIS 7000 Series

MULTI-TENANT DEDICATED PHONE LINE SYSTEM

- PROGRAMMABLE HANDS FREE SYSTEM
- PROGRAMMABLE 4-DIGIT ACCESS CODES
- CELLULAR PHONE COMPATIBLE
- POSTAL LOCK READY
- SINGLE LINE BACKLIT ELECTRONIC DIRECTORY LCD
- BUILT-IN NIGHT LIGHTS
- SINGLE RELAY
- BRUSH STAINLESS STEEL FACE-PLATE
- INDOOR OR OUTDOOR



SPECIFICATIONS

POWER INPUT: 12VAC/40VA (supplied) or 12VDC/40VA (output reading must be 13.5 - 14.5 VDC).
CURRENT CONSUMPTION: 500mA idle, 700mA operating.
EMERGENCY BATTERY: Built-in charging circuit for 12VDC/4Ahr rechargeable battery (battery is not supplied).
OPERATING ENVIRONMENT: 32°F to 140°F. Humidity 0%-95% non-condensing. **Heater is required if the temperature is below 32°F.**
MEMORY: EEPROM (non-volatile).

MOUNTING: Surface and full-flush.
DIMENSIONS:
Surface 10-13/16" (H) x 8-5/8" (W) x 3-3/4" (D).
Full-flush 10-13/16" (H) x 8-3/8" (W) x 2-7/16" (D)
MOUNTING RING FULL-FLUSH (FFM7 is included):
Inside 11-1/8" (H) x 8-11/16" (W) x 2-5/8" (D)
Outside 14-5/16" (H) x 12-1/8" (W)
Warranty: Two Years (24 months)

ORDER PART NUMBER

SURFACE MOUNT BRUSHED STAINLESS STEEL
7050 50 tenants and 50 access codes
7150 150 tenants and 150 access codes
7250 250 tenants and 250 access codes

FULL-FLUSH MOUNT BRUSHED STAINLESS STEEL
7050FF 50 tenants and 50 access codes
7150FF 150 tenants and 150 access codes
7250FF 250 tenants and 250 access codes
Mounting Ring (FFM7) is included.

ACCESSORIES

[Radio Receiver and Transmitter](#)
ARFR Radio Frequency Receiver
ARFT Radio Frequency Transmitter
ARFHT Radio Frequency Handheld Transmitter.

[Pedestal Mounting Post, Adapter Plate and Mounting Ring](#)
APM1 Pedestal Mounting Post.
APM2 Double arm mounting base plate for auto, pedestrian and semi-truck.
APM3 Pedestal mounting post for semi-truck.
APM5 Double arm side by side mounting base plate.
APMDB1 Direct Burial Pedestal Mounting Post.

[Video Package](#)
AVPC AeGIS Color Video Package.

[Miscellaneous Accessories](#)
AP7 Adapter Plate for installation with APM1, APMDB1, APM2, APM3, and APM5.
FFM7 Full-flush mounting ring, included with full-flush system.
ASP1 AC and Telephone Surge Protector.
AHP5 Heater Pad with Thermostat.
ABAT1 12VDC 4.5 Ahr backup battery.
ABHSE7 Battery Housing.
ARIGB7 Rough-in box.

Specifications and Warranty subject to change without prior notice

AeGIS ACCESS CONTROL
www.pach-co.com

941 Calle Negocio
San Clemente, CA 92673

Phone: 888-678-7224
Fax: 949-498-6879